Joystick, with one operating point per operating direction, With plastic shaft, 2 positions, Bezel: titanium, momentary, Vertical



Part no. M22-WJ2V

289196

EL Number

4315310

(Norway)

Product name Part no. EAN	Eaton Moeller® series M22 Joystick M22-WJ2V
Part no.	
	M22-WJ2V
EAN	
	4015082891961
Product Length/Depth	100 millimetre
Product height	30 millimetre
Product width	30 millimetre
Product weight	0.028 kilogram
Compliances	CE Marked
Certifications	CSA Std. C22.2 No. 94-91 CSA Std. C22.2 No. 14-05 IEC 60947-5 UL 508 EN 60947-5 VDE IEC/EN 60947-5 CSA CSA File No.: 012528 CSA-C22.2 No. 14-05 UL Category Control No.: NKCR CE CSA Class No.: 3211-03 IEC/EN 60947 CSA-C22.2 No. 94-91 UL File No.: E29184 UL VDE 0660
Product Tradename	M22
Product Type	Joystick
Product Sub Type	None
Bezel color	Titanium
Bezel material	Plastic
Fitted with:	Plastic shaft Filament bulb (24 V) Front ring Retraction in 0-position
Accessories	Plastic shaft
Degree of protection	IP66 NEMA 4X, 13
Lifespan, mechanical	100,000 Operations
Opening diameter	22.5 mm
Operating frequency	2000 Operations/h
Туре	Joystick
Mounting position	As required
Shock resistance	Mechanical, According to IEC/EN 60068-2-27 30 g, Mechanical, According to IEC/EN 60068-2-27, Sinusoidal shock 11 ms
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Rated operational current (Ie) at AC-21, 400 V, 415 V	0 A

Connection to SmartWire-DT	With SWD-RMQ connections Yes
Actuating force	5 N
Actuator function	Vertical Momentary
Number of actuation directions	2
Force for positive opening - min	0 N
Equipment heat dissipation, current-dependent Pvid	0 W
Heat dissipation capacity Pdiss	0 W
Heat dissipation per pole, current-dependent Pvid	0 W
Rated operational current for specified heat dissipation (In)	0 A
Static heat dissipation, non-current-dependent Pvs	0 W
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Please enquire
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	Not applicable.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 8.0**

Low-voltage industrial components (EG000017) / Control switch, Joystick (EC000632)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Control switch, joystick (ecl@ss10.0.1-27-37-14-04 [AKF061013])

Centre mounting, hole diameter  Dy stick length  Mmm  To  Number of actuation directions  Number of switch positions  Number of normally open contacts per actuation direction  Number of normally closed contacts per actuation direction  Number of make-and-break contacts per direction  With retraction in 0-position  Locking in 0-position  Mmm  22.5  2  2  2  2  2  2  3  4  5  6  7  7  8  7  8  7  8  8  8  8  8  8  8	(ecl@ss10.0.1-27-37-14-04 [AKF061013])		
Joy stick length  Number of actuation directions  Number of switch positions  Number of normally open contacts per actuation direction  Number of normally closed contacts per actuation direction  Number of make-and-break contacts per actuation direction  Number of make-and-break contacts per direction  With retraction in 0-position  Locking in 0-position  Coder  Analogue output signal configurable  With front ring  mm 75  2  2  2  3  4  5  6  7  7  8  7  8  7  8  7  8  7  8  7  8  7  8  7  8  7  8  7  8  8	Rated operation current le at AC-21, 400 V	Α	0
Number of actuation directions  Number of switch positions  Number of normally open contacts per actuation direction  Number of normally closed contacts per actuation direction  Number of make-and-break contacts per direction  With retraction in 0-position  Locking in 0-position  Coder  Analogue output signal configurable  With front ring  Analogue output signal configurable  With front ring  Analogue output signal configurable  No  Yes	Centre mounting, hole diameter	mm	22.5
Number of switch positions  Number of normally open contacts per actuation direction  Number of normally closed contacts per actuation direction  Number of make-and-break contacts per direction  With retraction in 0-position  Locking in 0-position  Coder  Analogue output signal configurable  With front ring  I a l a l a l a l a l a l a l a l a l a	Joy stick length	mm	75
Number of normally open contacts per actuation direction  Number of normally closed contacts per actuation direction  Number of make-and-break contacts per direction  Number of make-and-break contacts per direction  With retraction in 0-position  Locking in 0-position  Coder  Analogue output signal configurable  With front ring  No  Yes  Yes	Number of actuation directions		2
Number of normally closed contacts per actuation direction     0       Number of make-and-break contacts per direction     0       With retraction in 0-position     Yes       Locking in 0-position     No       Coder     No       Analogue output signal configurable     No       With front ring     Yes	Number of switch positions		1
Number of make-and-break contacts per direction 0 With retraction in 0-position Yes Locking in 0-position No Coder No Analogue output signal configurable No With front ring Yes	Number of normally open contacts per actuation direction		0
With retraction in 0-position  Locking in 0-position  Coder  Analogue output signal configurable  With front ring  Yes  No  No  Yes	Number of normally closed contacts per actuation direction		0
Locking in 0-position Coder Analogue output signal configurable With front ring  No Yes	Number of make-and-break contacts per direction		0
Coder No Analogue output signal configurable No With front ring Yes	With retraction in 0-position		Yes
Analogue output signal configurable  No With front ring  Yes	Locking in 0-position		No
With front ring Yes	Coder		No
	Analogue output signal configurable		No
Material front ring Plastic	With front ring		Yes
	Material front ring		Plastic

Colour front ring	Titanium
Degree of protection (IP)	IP66
Degree of protection (NEMA)	4X, 13